



Europäisches Patentamt
European Patent Office
Office européen des brevets



Publication number:

0 429 217 A2

EUROPEAN PATENT APPLICATION

Application number: 90312188.7

Int. Cl. 5: **H03L 7/197**

Date of filing: 07.11.90

Priority: 22.11.89 GB 8926358.

Date of publication of application:
29.05.91 Bulletin 91/22

Designated Contracting States:
DE FR GB IT SE

Applicant: **STC PLC**
1B Portland Place
London W1N 3AA(GB)

Inventor: **Gaskell, Philip Stuart**
20 Courtyards
Little Shelford, Cambridge CB2 5ER(GB)

Inventor: **Breakenridge, Eric**
64 Joyners Field
Harlow, Essex CM18 7PY(GB)

Inventor: **King, Nigel Jonathan Richard**
Culverwood, Rattery
South Brent, Devon TQ10 9LF(GB)


Inventor: **Ball, Michael John**
10 Lindsey Road
Bishop's Stortford, Herts CM23 2TA(GB)

Representative: **Dennis, Mark Charles et al**
STC Patents West Road
Harlow Essex CM20 2SH(GB)

Frequency synthesiser.

A fractional-N frequency synthesiser having a programmable divider and control means therefor, wherein said control means incorporates a digital delta-sigma modulator operating as an interpolator.

Fig. 1.



FREQUENCY SYNTHESISER

This invention relates to frequency synthesisers of the type in which a phase locked loop incorporates a programmable multi-modulus frequency divider the control input of which is switched between two or more integer values determined by a digital control circuit.

The output frequency of a phase-locked loop frequency synthesiser depends on the reference frequency and the division ratio:

$$f_{\text{out}} = N \cdot f_{\text{ref}}$$

where N is an integer

f_{out} = output frequency

f_{ref} = reference frequency

For fine frequency resolution, N may be increased and f_{ref} reduced but this gives rise to increased phase noise due to the higher division ratio and reduced frequency switching speed because of the lower loop bandwidth. An alternative technique is to switch N between two or more integer levels such that the average value of N is fractional. Such a synthesiser is often referred to as a 'fractional-N synthesiser' and can be considered as a method of interpolating a fractional number from integer values, hence the term 'Interpolating Synthesiser'. The interpolation algorithm is critical to minimising spurious signals and phase noise. Such a synthesiser is disclosed in British patent No. 2026268.

The general architecture of an interpolating synthesiser is shown in Fig. 1. The output frequency from a voltage controlled oscillator (VCO) 10 is divided by a programmable divider 11 and compared with the output of a reference oscillator 12 using a phase detector 13. The output error signal is filtered in a low pass filter 14 and the resultant signal controls the frequency of the VCO. If the control signal N were fixed, this would represent a standard phase-lock loop. In an interpolating synthesiser, the control signal is switched between two or more integer values determined by a digital control circuit. The control circuit may be split into several components. A logic circuit 16 converts an input number F, representing the desired frequency, into an integer number P and a fractional number M. An interpolator circuit 15 converts M into a data stream $M'(nT)$, at the reference frequency clock rate, where M' at any time nT takes one of two or more integer values. The average value of $M'(nT)$ is M. M' is then combined with P to form a data stream, $N(nT)$ at the reference frequency clock rate. In its simplest form the combiner is simply an adder. The average value of N is such that

$$F_{\text{out}} = F_{\text{ref}} \times N(nT)$$

If a poor interpolation algorithm is used, then it may be necessary to correct for interpolation errors by calculating, converting to analogue (via a digital-to-analogue converter) and, adding by means of circuit 17 the error signal to the output of the phase comparator. Depending on the nature of the interpolator, the error signal may need to be differentiated prior to addition to the phase detector output. In some practical systems, generating the error signal accurately is a difficult process because of the required high speeds and high accuracy of the digital-to-analogue converter.

According to the present invention there is provided a fractional-N frequency synthesiser having a programmable divider and control means therefor, wherein said control means incorporates a digital delta-sigma based modulator operating as an interpolator.

Embodiments of the invention will now be described with reference to the accompanying drawings in which:-

Fig. 1 illustrates in block schematic form the general architecture of a single loop interpolating synthesiser,

Fig. 2 illustrates a first order interpolator,

Fig. 3 illustrates a single loop feedback second order interpolator,

Fig. 4 illustrates a dual loop, feedback second order, interpolator,

Fig. 5 illustrates a third order interpolator with a first order feed-forward loop,

Fig. 6 illustrates a multi-stage interpolator,

Fig. 7 illustrates an interpolator with a second order delta-sigma modulator and a down sampling decimation filter,

Fig. 8 illustrates an error compensating interpolating synthesiser, and

Fig. 9 illustrates an error compensating interpolating synthesiser with a second order, dual loop interpolator.

The form of interpolation utilised in the present invention employs principles similar to those underlying oversampling noise-shaping analogue-to-digital coders (ADC). Such an ADC is disclosed in, for example, British Patent 1 450 989 and are generally referred to as delta-sigma coders or modulators.

These coders or modulators have traditionally been associated with A/D conversion where oversampling and noise-shaping are used to force the error signal due to a coarse conversion stage outside the wanted signal band. This gives a rising noise and distortion profile with frequency. In an interpolating synthesiser, the goal is to ensure that, within the closed loop bandwidth, the noise and spuri from the interpolator are low; at larger offsets, higher levels of noise and spuri from the interpolator are rejected by the low pass filtering action of the loop. Whereas the noise-shaping coder for an ADC is analogue, the modulator for the synthesiser is digital.

The main advantages of this technique for a synthesiser are:

- low phase noise
- low levels of spurious signals
- error correcting digital-to-analogue converter (DAC) may be omitted
- wider closed loop bandwidth giving improved frequency agility.

Current fractional-N synthesisers have control circuits consisting of one or more accumulators in series whose respective carry bits are used to control the division ratio of the frequency divider. In the proposed invention the basic control element is a first or second order feedback noise-shaping modulator; higher orders can be realised by the addition of further first- or second- order modulators in a feed-forward arrangement.

The simplest form of the control circuit interpolator is a first order feedback modulator similar in concept to a digital sigma-delta modulator Fig. 2. This consists of a coarse (normally one-bit) quantiser 21 preceded by a first order integrator 22. Negative feedback is applied from the output of the quantiser to the input of the modulator. This circuit is liable to have poor noise rejection and high spuri and the second-order equivalent is in practice more useful.

The second order modulator can be configured as a single loop with a single second-order filter 31 (Fig. 3) or a double feedback loop with two first order integrators 41, 42 (Fig. 4). There are a number of possible variants of the basic circuit where extra unit delays or additional gain stages are included. Taking the double loop circuit (Fig. 4) as an example, the core of the modulator is a coarse resolution quantiser 40 (usually one-bit but it could be more) preceded by a first-order digital integrator 42. The Q output from the quantiser is fed back to the integrator input to form an inner loop. The inner loop itself is located in an outer loop incorporating another first order integrator 41. The input to the modulator is a multi-bit word with adequate precision to give the final required frequency resolution.

The transfer function is conveniently described in the z-domain:

$$Y(z) = z^{-1}X(z) + (1 - z^{-1})^2 E(z) \quad (1)$$

This shows that the wanted signal has unity gain plus a unit delay, and that the core quantising noise $E(z)$ is shaped by a second order function $(1 - z^{-1})^2$. $E(z)$ is the quantisation noise from the modulator, and has an essentially white spectrum.

The noise rejection of the basic second-order circuit can be improved by feeding the quantisation error signal from the first stage 50 forward to a further first or second order stage 51 (see Fig. 5). The output from the second stage is recombined with that of the first stage. Since the error signal fed forward to the second stage is the unweighted (i.e. white) quantisation noise, the output from the second stage has to be weighted in the same manner as in the first stage, before it can be combined with the first stage output.

Again, there are several variants of the basic high order feed-forward circuit. Taking the third order circuit shown in Fig. 5 as an example, the output from the first stage is

$$Y_1(z) = z^{-1}X(z) + (1 - z^{-1})^2 E_1(z) \quad (2)$$

and the error signal fed to the second stage is $-E_1(z)$. The output from the second stage is given by

$$Y_2(z) = E_1(z) + (1 - z^{-1}) E_2(z) \quad (3)$$

Since the first stage error signal has a second order frequency weighting, the second stage output must be weighted in line with the first stage output:

$$Y_2(z) = (1 - z^{-1})^2 E_1(z) + (1 - z^{-1})^3 E_2(z) \quad (4)$$

After combination with the first stage the final output is:-

$$Y(z) = z^{-1}X(z) + (1 - z^{-1})^3 E_2(z) \quad (5)$$

Since $E(z)$ has an approximately white spectral characteristic, Equation 5 shows that the resultant overall error signal has a third order characteristic and the wanted signal has a flat transfer function. In-band spuri are likewise suppressed by the high loop gain implicit in the third order circuit. The reduced in-band noise and spuri from the interpolator translates to lower close-in phase-noise and spuri from the synthesiser.

When the stage outputs are re-combined, the interpolator produces a multi-bit output which drives a programmable divider in the loop. For the 3rd order circuit, there are six possible output levels and 6-division ratios.

These same feed-forward principles can be extended to fourth and higher order implementations (see

Fig. 6). The second and subsequent stages can be a combination of first or second order stages.

An alternative method of generating the interpolating switching signal is to start with a sampling frequency which is a multiple of the reference frequency ($K \cdot f_{ref}$) and to decimate down to the reference frequency or a sub-multiple of the reference frequency. The basic structure is shown in Fig. 7. As shown in Fig. 7 the output of a second order modulator 70, at frequency ($k \cdot f_{ref}$), is applied to a decimation filter 71 where it is decimated down to either f_{ref} or $f_{ref}/1$.

The basic principle stems from the frequency domain representation of the interpolator noise output function, $(1 - z^{-1})^2 E(z)$, given by

$$N(f) = (1 - \cos(2\pi f / f_s)) \cdot E(f) \quad (6)$$

$N(f)$ has a null around $f = 0$ Hz, the width of which (for a given attenuation) is proportional to the sampling frequency f_s . If the initial modulation can be performed at some higher sampling frequency, before re-sampling at the reference frequency in a manner that does not increase the noise, then the increased noise free bandwidth of the initial modulation can be utilised.

The process of re-sampling without increasing the noise is called decimation. The process involves filtering the signal and then down-sampling the filter output. A suitable filter for a second-order modulator is one with the transfer function:

$$H(z) = \frac{(1 - z^{-n})^3}{(1 - z^{-1})} \quad (7)$$

A filter of this type involves accumulation, which in turn increases the number of bits needed to represent a sample. In general, any decimation filtering will increase the number of bits needed to represent the signal. It is therefore necessary to provide a programmable divider circuit in the synthesiser in order to use this method.

If the in-band error signal is too large causing excess noise or spurs, it can be compensated for by extracting the error signal from the interpolator 80, converting it to analogue in DAC 81 and adding it to the output of the phase comparator 82 (see Fig. 8). Since the phase is the integral of frequency and the interpolator controls the frequency rather than the phase, the error signal may have to be passed through frequencyweighting network 83 prior to addition to the phase comparator output. This will depend from where in the interpolator the error signal is extracted.

An example of such an arrangement for a second-order interpolator is shown in Fig. 9. The error between the output and the input is given by

$$Y(z) - z^{-1}X(z) = (1 - z^{-1})^2 E(z) \quad (8)$$

This corresponds to the error in frequency of the divider output. $E(z)$ is the double integral of this error and corresponds to the integral of the phase error. The phase error from the interpolator can therefore be compensated for by converting $E(z)$ i.e. the quantisation error, Q , to the analogue domain via a DAC, differentiating it and adding it to the phase comparator output as shown in Fig. 8. The advantage of differentiating the DAC output is that it provides DC blocking and a low DC-offset DAC is not required.

The output from the second integrator of the modulator is

$$Y_2(z) = z^{-1}X(z) + (z^{-2} - 2z^{-1})E(z) \quad (9)$$

Therefore:

$$Y_2(z) - Y(z) = -E(z) \quad (10)$$

i.e. $-Q(t) = y_2(t) - y(t)$ in the time domain.

This relationship is the same as that derived for the higher order feed-forward coders described earlier and is easily implemented as shown in Fig. 8.

Claims

1. A fractional-N frequency synthesiser having a programmable divider and control means therefor, characterised in that said control means incorporates a digital delta-sigma modulator operating as an interpolator.
2. A synthesiser according to claim 1 characterised in that said delta-sigma modulator is a second-order feedback modulator.
3. A synthesiser according to claim 2 including at least one additional first or higher order loop(s) to the

modulator configured in a feed-forward arrangement.

4. A synthesiser according to any preceding claim wherein the interpolator sampling frequency is a multiple of the synthesiser reference frequency, the synthesiser including means for sub-sampling the interpolator at the reference frequency.
5. A synthesiser according to any preceding claim including means for extracting an error signal from the interpolator output, means for filtering the error signal, means for converting the filtered error signal to an analogue signal and means for adding the analogue to the synthesiser phase comparator output.
6. A synthesiser according to any preceding claim wherein the synthesiser is a multiple-loop synthesiser.

10

15

20

25

30

35

40

45

50

55




Fig. 2.




Fig. 3.




Fig. 4.




Fig. 5.




Fig. 6.




Fig. 7.




Fig. 8.





Fig. 9.



(19)



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) Publication number:

0 429 217 A3

(12)

EUROPEAN PATENT APPLICATION

(21) Application number: 90312188.7

(51) Int. Cl.⁵: **H03L 7/197**

(22) Date of filing: 07.11.90

(30) Priority: 22.11.89 GB 8926358

(43) Date of publication of application:
29.05.91 Bulletin 91/22(84) Designated Contracting States:
DE FR GB IT SE(88) Date of deferred publication of the search report:
02.10.91 Bulletin 91/40(71) Applicant: **STC PLC**
1B Portland Place
London W1N 3AA(GB)


(72) Inventor: **Gaskell, Philip Stuart**
20 Courtyards
Little Shelford, Cambridge CB2 5ER(GB)
Inventor: **Breakenridge, Eric**
Basscrest House, 40a Grange Road
Alloa FK10 1LR, Scotland(GB)
Inventor: **King, Nigel Jonathan Richard**
Culverwood, Rattery
South Brent, Devon TQ10 9LF(GB)
Inventor: **Ball, Michael John**
10 Lindsey Road
Bishop's Stortford, Herts CM23 2TA(GB)

(74) Representative: **Dennis, Mark Charles et al**
Northern Telecom Europe Limited Patents
and Licensing West Road
Harlow Essex CM20 2SH(GB)

(54) **Frequency synthesiser.**

(57) A fractional-N frequency synthesiser having a programmable divider and control means therefor,

wherein said control means incorporates a digital delta-sigma modulator operating as an interpolator.

Fig. 1.



European
Patent Office

EUROPEAN SEARCH REPORT

Application Number

EP 90 31 2188

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int. Cl.5)
Y	EP-A-0 308 194 (MATSUSHITA) * column 2, line 24 - column 3, line 19 * - - -	1,2,5	H 03 L 7/197 H 03 M 3/02
Y,D	GB-A-2 026 268 (RACAL COMMUNICATIONS EQUIPMENT LTD) * abstract; figure 3 * - - - - -	1,2,5	
			TECHNICAL FIELDS SEARCHED (Int. Cl.5)
			H 03 L H 03 M
The present search report has been drawn up for all claims			
Place of search The Hague		Date of completion of search 08 August 91	Examiner PEETERS M.M.G.
<div>CATEGORY OF CITED DOCUMENTS</div> <div>X: particularly relevant if taken alone Y: particularly relevant if combined with another document of the same category A: technological background O: non-written disclosure P: intermediate document T: theory or principle underlying the invention</div> <div>E: earlier patent document, but published on, or after the filing date D: document cited in the application L: document cited for other reasons ----- &: member of the same patent family, corresponding document</div>			